

Bariera optoelektroniczna, jednokierunkowa, seria BOS (BOS0284) - Balluff



Numer artykułu SKU:
OC-BALLUFF003772

Numer artykułu producenta:

Tylko na zamówienie

BALLUFF

OPIS PRODUKTU

Charakterystyka

Cechy szczególne	Washdown Plus, Washdown
Seria	R080K
Wymiary	19 x 44.2 x 37.5 mm
Interfejs	IO-Link 1.1, Analogowy, prąd 4...20 mA
Pin 4	Push-pull Styk zwierny/rozwierny (NO/NC)
Pin 2	PNP/NPN/push-pull Styk zwierny/rozwierny (NO/NC)
Zasada działania	Czujnik optoelektroniczny
Zasada działania optycznego	Bariera jednokierunkowa (odbiornik)
Rodzaj światła	Światło czerwone
Zasięg	0... 20 m
Przyłącze	Złącza wtykowe, M12x1-Męski, 4-stykowe
Materiał obudowy	PA 12 PA PACM 12
Materiał powierzchni aktywnej	PA PACM 12
Napięcie robocze Ub	10...30 VDC
Dopuszczenie / Zgodność	CE, UKCA, WEEE, cULus, Ecolab

Secondary features	Identification, Device Discovery, Switching Profiles, Signal Quality Monitoring, External Signal Blanking, Signal Delay, Signal Speed Monitor, Switching Counter, Basic Statistics, Logic Blocks, Operating Hours Counter, Boot Cycle Counter, Voltage and Current Monitoring, Extreme Environment Status, Storage Usage Monitoring, Variant Configuration, Pin Assignment
Secondary features for condition monitoring	Vibration monitoring, Inclination monitoring and installation aid, Internal temperature monitoring, Internal humidity detection
Zakres dostawy	Wskazówka montażowa

DANE TECHNICZNE

Nr kat.	OC-BALLUFF003772
---------	------------------